

# Firmware Release Note

**SAMSUNG**  
BUSINESS

<b>Model : CLX-4195N. FN</b>	<b>Date:</b>	<b>May 18, 2015</b>
------------------------------	--------------	---------------------

<b>Version</b>	<b>Category</b>	<b>Change Description</b>
<b>V4.xx.01.58</b> (20-May, 2014)	Fix Defect	- Fix the USB scan to PC issue - Fix the Auto Color Registration fail - Improve connection of C3N USB device in special case - Gigabit Network Connection Error
<b>V4.xx.02.16</b> (11-Dec, 2014)	Fix Defect	Add the new error code(M3-1112, Jam Inside of Machine)
		Fix the PCL error issue
		Fix PDF direct print issue
		Photo Print Quality & Copy Text Improvement
		Improve the paper curl
<b>V4.xx.03.06</b> (May-14, 2015)	Add Func.	Apply PostScript

## ※ Note

- Please do not turn off the printer and your computer until firmware update finishes.
- If you are using USB connection, disconnect all other USB printers from the PC.
- The firmware update you are about to install has been tested for compatibility with Samsung toner cartridge products ONLY.  
Installing The upgrade may cause a non-Samsung toner cartridge to malfunction.
- Do not run your printer during the firmware update.(Do not have any print job)

## How to update the firmware using a USB cable.


**1. Make sure that the machine is connected to the PC with a USB cable.**

**2. Check the current firmware version of your printer.**

- If the firmware version is V4.xx.01.48 and more lower,  
Execute a patch file(C LX4195FN\_UpgradeJig.exe)  
And then patch rom will be download on the machine.  
Please wait until green LED is ON.(About 2~3 minutes)
- If the firmware version is V4.xx.01.49 and more higher, Go to next step.

**3. Drag the firmware file(\*.hd) and Drop down it on usblist2.exe.**

And then, firmware update will be started automatically.



## How to update the firmware for a network connected printer.

**1. Check the current firmware version of your printer.**

- If the firmware version is V4.xx.01.48 and more lower,  
Execute a patch file(C LX4195FN\_UpgradeJig.exe)  
And then patch rom will be download on the machine.  
Please wait until green LED is ON.(About 2~3 minutes)
- If the firmware version is V4.xx.01.49 and more higher, Go to next step.

**2. Open Internet Explorer and enter the IP address of your printer.**

**3. Go to the SyncThruWeb Service (SWS) main home page.**

**Login as Admin in SyncThruWeb Service.**

NOTE: Login using the Administrator ID and Password established during initial machine setup.

**4. Click [Maintenance] on the top menu.**

And then click [Firmware Upgrade] or Application Management > Application

**5. Click Add button**

**6. Click [Browse].**

**Choose installation file by browsing file system. And click OK button**

**7. The firmware update will start.**

Once the f/w update is complete, the machine power-off and power-on automatically.